

*The **Oticon ConnectLine Phone Adapter** is an interface between a conventional landline phone installation and the Oticon Streamer Pro or the Oticon ConnectClip\*, in effect turning a pair of Oticon hearing instruments into a wireless headset.*

*As part of the ConnectLine system, the Phone Adapter works seamlessly and simultaneously with other ConnectLine solutions such as mobile phones, TV and the ConnectLine Microphone.*

### **A fully integrated system**

With ConnectLine the user is in control of the system, not the other way around. Advanced features such as AutoPriority and AutoConnect ensure that the user can hear and answer a phone call while watching TV.

### **Landline home phone**

Phone Adapter 2.0 is installed in parallel to an existing landline home phone installation.

Once a user is in range of the Phone Adapter, the Streamer Pro or ConnectClip is automatically connected and ready to receive calls (AutoConnect).

The call can easily be answered, with a single touch of a button on the Streamer Pro, at a distance of up to 30 meters/98 ft. from the Phone Adapter. From the ConnectClip, the call is answered by briefly pressing the multi-button.

### **AutoPriority**

If a user is listening to the TV using the ConnectLine TV solution (or other audio sources), the AutoPriority feature ensures that an incoming call is notified.

### **AutoResume**

Once the call is ended the Streamer Pro or ConnectClip automatically resumes to its previous state for example, back to the TV input if a call was taken while watching TV.

For more information please refer to:  
[www.oticon.com/support](http://www.oticon.com/support)



\* Both Oticon Streamer Pro and ConnectClip can be paired with the Phone Adapter, but they will not work simultaneously. It is therefore recommended only to pair one at a time.

### Included

- RJ11 – RJ11 cable for connection to landline home phone
- Power supply
- Instructions for use



Technical data	
Product and Model name	ConnectLine Phone Adapter 2.0, Model BS-H200
Compatibility	Streamer Pro 1.4 and later, and ConnectClip 1.0 and later
Dimensions	124 x 80 x 21 mm; weight 100 g.
ConnectLine system features	AutoConnect: Will automatically connect to the Streamer Pro or ConnectClip when in range. AutoPriority: Incoming calls will be prioritized over e.g. TV sound. Proximity pairing: The phone adapter will automatically pair to the Streamer Pro or ConnectClip if the Streamer Pro or ConnectClip is in pairing mode.
Range	Up to 30 meters /98 ft. with Streamer Pro or ConnectClip (free line of sight)
Connections	Phone line in/out for interface to analog landline home phone (PSTN) (RJ11/RJ11) ConnectLine in/out for direct interface to e.g. computer1
Power consumption	Max. 190 mA (using the included power supply)
Headset in	Max 6dBmV(RMS), 10 K $\Omega$
Headset out	-15 – -10dBmV(RMS), 10 -100 $\Omega$
Audio Bandwidth	License free 2.4 GHz (ISM band)
AutoConnect (range)	Yes (30 meters/98 ft.)
Audio Quality	Mono / 8 kHz sample frq
Frequency	80 Hz - 3.5 kHz (wireless)
Operating temperature	10 to 40°C / 50 to 104°F
Storage temperature	-20 to 70 °C / -4 to 158°F
Emissions	Max. 39 dB $\mu$ V/m @ 3 meters. In compliance with all relevant standards

### References:

1. A Computer interface cable is included with Streamer Pro and ConnectClip. Also available as an accessory.